

SLA

READY TO START

Ready to use, SLA batteries (AGM technology) are **Factory Activated**, **completely spill-proof**, and **require no maintenance**. Our SLA offer is the **widest ready to use** range available on the market. This range of batteries is the perfect solution for **budget-conscious riders looking for performance and time-saving (efficiency)**.



FACTORY ACTIVATED

AGM (Absorbent Glass Mat) technology.



READY TO USE

Just plug & play.



NO MAINTENANCE

VRLA (Valve Regulated Lead Acid) design.



SPILL-PROOF DESIGN

Factory sealed & electrolyte held in a glass fiber mat.



NO ACID HANDLING


Very safe.



HIGH STARTING POWER & EXTENDED CYCLE LIFE

MOUNTING ANGLES

HIGH INCLINATION
NON-SPILLABLE



COMPATIBLE CHARGERS

BS 10 Battery size up to 20Ah	BS 15 Battery size up to 30Ah
BS 30 Battery size up to 60Ah	BS 30 MAX Battery size up to 60Ah
BS 60 Battery size up to 120Ah	BK 20 Battery size up to 40Ah

DID YOU KNOW?

SLA range can replace 95% of Maintenance Free and DRY batteries.

SLA batteries are non-spillable, so they're safe to ship and e-commerce ready!



BS BATTERY TYPE	BS CODE	CAPACITY Ah (10Hr)	CAPACITY Ah (20Hr)	CCA A (-18°C)	DIMENSIONS (±2mm)			ASSEMBLY LAYOUT	TERMINAL
					L	W	H		
BTZ7S	300635-1	6	6.3	130	113	70	105		A
BT7B-4	300641	6.5	6.8	110	150	65	93		A
BTZ7V	300912	6.5	6.8	105	113	70	121		A
BTZ8V	300890	7	7.4	120	113	70	130		A
BT9B-4	300642	8	8.4	120	150	68	105		A
BTZ10S	300636-1	8.6	9	190	150	88	93		A
BT12-10Z	300913	10	10.5	180	194	59	112		A
BTZ12S	300637-1	11	11.6	215	150	88	110		A
BT12B-4	300643	10	10.5	210	150	69	130		A
BTZ14S	300638-1	11.2	11.8	230	150	88	110		A
BT14B-4	300644	12	12.6	210	150	69	145		A
BT4B-5	300756	2.3	2.4	40	113	38	85		J
BTR4A-5	300667	2.3	2.4	35	113	48	85		I
BTX4L+/BTZ5S	300669	4	4.2	65	113	70	85		A
BTX5L/BTZ6S	300670	5	5.3	90	113	70	105		A
BTX6.5L	300904	6.5	6.8	85	139	66	100		B
BTX7L	300673	6	6.3	100	113	70	130		A
BTX7A	300672	6	6.3	105	150	87	93		A
BTX9	300674	8	8.4	135	150	87	105		A
BT12A	300679	10	10.5	175	150	87	105		A
BTX12	300680	10	10.5	180	150	87	130		A
BTX14	300681	12	12.6	200	150	87	145		A
BTX14L	300760	12	12.6	200	150	87	145		A
BTX14AH/BB14-A2/B2	300758	14	14.7	210	135	90	164		A
BTX14AHL/BB14L-A2/B2	300759	14	14.7	210	135	90	164		A
BTX16	300763	14	14.7	230	150	87	161		A
BTX20CH	300766	18	18.9	270	150	87	161		A
BTX20H	300688	18	18.9	310	175	87	155		A
BTX20HL	300689	18	18.9	310	175	87	155		A
BTX24HL/B50-N18L-A/A2/A3	300770	21	22.1	350	205	87	162		A
BIX30L	300631	30	31.6	400	165	125	175		A
12N5.5-3B	300840	5.5	5.8	70	135	60	130		A
12N5.5-4A/4B	300841	5.5	5.8	70	135	60	130		A
12N7A-3A/B	300683	10	10.5	90	146	60	130		B
BB3L-A/B	300842	3	3.2	35	98	56	110		B
BB4L-B	300665	4	4.2	50	120	70	92		A
BB5L-B	300671	5	5.3	65	120	60	130		B
BB7-A	300850	8	8.4	120	135	75	133		A
BB7C-A	300843	8	8.4	80	129	89	114		B
BB7L-B2	300836	8	8.4	100	135	75	133		E
BB9-B	300675	9	9.5	120	135	75	139		A
BB10L-A2/B2	300677	11	11.6	120	133	90	145		A
BB12AL-A2	300837	12	12.6	150	134	80	161		B
BB12A-A/B	300881	12	12.6	150	134	80	161		B
BB14A-A2	300838	14	14.7	200	134	88	176		A
BB16AL-A2	300839	16	16.8	160	205	70	162		A
BB16CL-B	300771	19	20	230	175	100	175		A
53030	300880	30	31.6	300	178	123	166		G
6N4-2A/A-4	300916	4	4.2	25	71	71	93		-
6N6-3B/B-1	300917	6	6.3	50	95	55	117		B
B49-6	300918	10	10.5	80	91	83	159		B
B38-6A	300919	13	13.7	105	119	83	161		B
6N11A-1B/3A	300915	11	11.6	90	121	58	130		B
6N11A-4A	300914	11	11.6	90	121	58	130		B

12V

6V

TERMINAL
TYPE

A



B



C



D



E



F



G



H



I



J



BATTERY RANGE OVERVIEW



DRY BATTERY

CONVENTIONAL



Entry-level bikers with standards requirement.

MF BATTERY

MAINTENANCE FREE



Entry-level bikers seeking easiness.

TECHNOLOGY

Flooded dry

AGM/VRLA

FACTORY ACTIVATED READY TO USE

—

—

NO ACID HANDLING

—

—

NO MAINTENANCE

—





NON-SPILLABLE

—

—

INCLINATION LEVEL



OEM APPROVED

—



SUITABLE FOR E-COMMERCE

COMPLIANT WITH EU REGULATION 2019/1148
(FOR THE SALE OF ACID FOR BATTERIES)

—

—

EASY TO SHIP

—

—

TRANSPORT TYPE



SLA
 FACTORY ACTIVATED

READY TO START



Budget-conscious riders looking for performance and time-saving.

SLA
 FACTORY ACTIVATED **MAX**

 READY TO START
 MAXIMUM POWER


Adventure riders with big engines seeking robust performance and durability.

LITHIUM
 LiFePO4

 INNOVATION FOR
 HIGH PERFORMANCE


Demanding riders seeking for peak performance, lightweight and advanced technology.

LITHIUM
 LiFePO4 **MAX**

 INNOVATION FOR
 MAXIMUM PERFORMANCE





Selective riders aiming to meet the latest standards of modern vehicles.

AGM/VRLA

AGM/VRLA

LiFePO4

LiFePO4



UPGRADE CROSS REFERENCE CHART

DRY	MF	SLA	SLA MAX	LITHIUM
	BTZ5S/BTX4L-BS+	BTZ5S/BTX4L+		BSLi-02 ; BSLi-02 MAX
		BTZ6S/BTX5L		BSLi-02 ; BSLi-02 MAX
	BTZ7S-BS	BTZ7S		BSLi-02 ; BSLi-02 MAX
	BT7B-BS	BT7B-4		BSLi-03
		BTZ7V		BSLi-02 ; BSLi-02 MAX
		BTZ8V		BSLi-02 ; BSLi-02 MAX
	BT9B-BS	BT9B-4		BSLi-03
	BTZ10S-BS	BTZ10S		BSLi-04/06
	BTZ12S-BS	BTZ12S		BSLi-04/06 ; BSLi-09
	BT12B-BS	BT12B-4		BSLi-04/06
	BTZ14S-BS	BTZ14S		BSLi-04/06 ; BSLi-09
	BT14B-BS	BT14B-4		BSLi-04/06
51814 ; 51913			51913 MAX	BSLi-12
	BT12-10Z-BS	BT12-10Z		
	BT4B-BS	BT4B-5		
	BTR4A-BS	BTR4A-5		
	BTX4L-BS+/BTZ5S-BS	BTX4L+/BTZ5S		BSLi-02 ; BSLi-02 MAX
	BTX5L-BS	BTX5L/BTZ6S		BSLi-02 ; BSLi-02 MAX
		BTX6.5L		BSLi-02 ; BSLi-02 MAX
	BTX7L-BS	BTX7L		BSLi-02 ; BSLi-02 MAX
	BTX7A-BS	BTX7A		BSLi-03
	BTX9-BS	BTX9		BSLi-03
	BT12A-BS	BT12A		BSLi-04/06
	BTX12-BS	BTX12		BSLi-04/06
	BTX14-BS	BTX14	BTX14H MAX ; BGZ16H MAX	BSLi-04/06
	BTX14L-BS	BTX14L	BGZ16HL MAX	BSLi-08
BB14-A2 (12N14-4A) ; BB14-B2	BTX14AH-BS	BTX14AH/BB14-A2/B2	BTX14AH MAX	BSLi-04/06
BB14L-A2 (12N14-3A) ; BB14L-B2	BTX14AHL-BS	BTX14AHL/BB14L-A2/B2		BSLi-05
	BTX16-BS	BTX16	BTX16H MAX	BSLi-09
	BTX20-BS	BTX20H	BGZ20H MAX	BSLi-09
	BTX20CH-BS ; BTX20A-BS	BTX20CH		BSLi-09
BB18L-A	BTX20L-BS ; BTX20HL-BS	BTX20HL	BGZ20HL MAX	BSLi-10 ; BSLi-10 MAX
B50-N18L-A/A2/A3	BTX24HL-BS	BTX24HL/B50-N18L-A/A2/A3		BSLi-10 ; BSLi-10 MAX
BB30L-B	BIX30L-BS	BIX30L	BGZ3ZHL MAX	BSLi-10 ; BSLi-10 MAX
6N11A-1B ; 6N11A-3A		6N11A-1B/3A		
6N4-2A ; 6N4-2A-4		6N4-2A/A-4		
6N6-3B ; 6N6-3B-1		6N6-3B/B-1		
6N11A-4 ; 6N11A-4A		6N11A-4A		
B49-6		B49-6		
B38-6A		B38-6A		
12N5.5-3B		12N5.5-3B		BSLi-02 ; BSLi-02 MAX
12N5.5-4A ; 12N5.5-4B		12N5.5-4A/4B		
12N7A-3A		12N7A-3A/B		
BB3L-A ; BB3L-B		BB3L-A/B		BSLi-01
BB4L-B		BB4L-B		BSLi-02 ; BSLi-02 MAX
BB5L-B (12N5-3B)		BB5L-B		BSLi-02
BB7-A (12N7-4A)		BB7-A		BSLi-03
BB7C-A		BB7C-A		BSLi-02 ; BSLi-02 MAX
BB7B-B		12N7A-3A/B		
BB7L-B (12N7-3B) ; BB7L-B2		BB7L-B2		BSLi-02 ; BSLi-02 MAX
BB9-B (12N9-4B-1)	BT9A-BS	BB9-B		BSLi-03
BB10L-A2 ; BB10L-B2 ; BB10L-BP		BB10L-A2/B2		BSLi-05
BB12AL-A/A2		BB12AL-A2		BSLi-05
BB12A-A (12N12A-4A-1) ; BB12A-B		BB12A-A/B		BSLi-04/06
BB14A-A2 ; BB14A-A1		BB14A-A2		BSLi-04/06
BB14-A2 (12N14-4A) ; BB14-B2	BTX14AH-BS	BB14-A2/B2/BTX14AH	BTX14AH MAX	BSLi-04/06
BB14L-A2 (12N14-3A) ; BB14L-B2	BTX14AHL-BS	BB14L-A2/B2/BTX14AHL		BSLi-05
BB16AL-A2		BB16AL-A2		BSLi-05
BB16CL-B		BB16CL-B		BSLi-10 ; BSLi-10 MAX
B50-N18L-A/A2/A3	BTX24HL-BS	B50-N18L-A/A2/A3/BTX24HL		BSLi-10 ; BSLi-10 MAX
53030		53030		BSLi-12 ; BSLi-12 MAX