



I-97015

8-channel RTD Input Module

Features

- 8-channel RTD Input
- 3-wire RTD Lead Resistance Elimination
- High Resolution: 16-bit
- Individual Channel Configuration
- Open Wire Detection
- Overvoltage Protection
- ± 4 kV ESD Protection
- 3000 VDC Intra-module Isolation



Introduction

The I-97015 is an 8-channel RTD input module for measuring temperature from RTD sensors. Each channel can be connected to different types of RTD sensor, and features automatic compensation for three-wire RTD so that accurate measurements can be made regardless of the length of the wires.

Open wire detection and overvoltage protection are also included, together with 4 kV ESD protection and 3000 VDC intra-module isolation.

System Specifications

LED Display	
Status	1 x Power and Communication 16 x High/Low Alarm Signals
Isolation	
Intra-module Isolation, Field-to-Logic	3000 VDC
EMS Protection	
ESD (IEC 61000-4-2)	± 4 kV Contact for Each Terminal ± 8 kV Air for Random Point
RS Immunity (IEC 61000-4-3)	3 V/m, 80 MHz ~ 1 GHz
COM Ports	
Ports	1 x RS-485
Baud Rate	1200 ~ 115200 bps
Data Format	N, 8, 1
Protocol	DCON
Power	
Consumption	0.6 W Max.
Mechanical	
Dimensions (W x L x H)	31 mm x 134 mm x 144 mm
Environment	
Operating Temperature	-25 ~ +75 °C
Storage Temperature	-40 ~ +85 °C
Humidity	10 ~ 90 % RH, Non-condensing

Applications

- Building Automation
- Factory Automation
- Machine Automation
- Remote Maintenance
- Remote Diagnosis
- Testing Equipment

I/O Specifications

Analog Input	
Channels	8
Sensor Type	Pt100, Pt1000, Ni100, Ni120, Cu50, Cu100, Cu1000
Resistance Measurement	3.2 k Ω
Resolution	16-bit
Accuracy	± 0.05 % of FSR
Sampling Rate	12 Hz (Total)
Bandwidth	15.7 Hz
Input Impedance	> 1 M Ω
Common Mode Rejection	150 dB
Normal Mode Rejection	100 dB
Overvoltage Protection	± 120 VDC
Individual Channel Configuration	Yes
Open Wire Detection	Yes
3-wire RTD Lead Resistance Elimination	Yes
Zero Drift	± 0.5 μ V/°C
Span Drift	± 20 ppm/°C

